



# MMBT3906

## PNP GENERAL PURPOSE SWITCHING TRANSISTOR

**VOLTAGE** 40 Volt **POWER** 330 mWatt

**SOT-23** Unit : inch(mm)

### FEATURES



- PNP epitaxial silicon, planar design
- Collector-emitter voltage  $V_{CE} = -40V$
- Collector current  $I_C = -200mA$
- Lead free in compliance with EU RoHS 2.0
- Green molding compound as per IEC 61249 standard

### MECHANICAL DATA

Case : SOT-23, Plastic

Terminals : Solderable per MIL-STD-750, Method 2026

Approx. Weight : 0.0084 grams



### ABSOLUTE RATINGS

Parameter	Symbol	Value	Units
Collector - Emitter Voltage	$V_{CEO}$	-40	V
Collector - Base Voltage	$V_{CBO}$	-40	V
Emitter - Base Voltage	$V_{EBO}$	-5	V
Collector Current - Continuous	$I_C$	-200	mA

### THERMAL CHARACTERISTICS

Parameter	Symbol	Value	Units
Max Power Dissipation (Note 1)	$P_{TOT}$	330	mW
Thermal Resistance , Junction to Ambient	$R_{\theta JA}$	375	$^{\circ}C/W$
Operating Junction Temperature and Storage Temperature Range	$T_J, T_{STG}$	-55 to 150	$^{\circ}C$

Note 1: Transistor mounted on FR-5 board 1 x 0.75 x 0.062 in.





# MMBT3906

## ELECTRICAL CHARACTERISTICS

Parameter	Symbol	Test Condition	MIN.	TYP.	MAX.	Units
Collector - Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = -1mA, I_B = 0$	-40	-	-	V
Collector - Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C = -10\mu A, I_E = 0$	-40	-	-	V
Emitter - Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E = -10\mu A, I_C = 0$	-5	-	-	V
Base Cutoff Current	$I_{BL}$	$V_{CE} = -30V, V_{EB} = -3V$	-	-	-50	nA
Collector Cutoff Current	$I_{CEX}$	$V_{CE} = -30V, V_{EB} = -3V$	-	-	-50	nA
DC Current Gain (Note 2)	$h_{FE}$	$I_C = -0.1mA, V_{CE} = -1V$	60	-	-	-
		$I_C = -1mA, V_{CE} = -1V$	80	-	-	
		$I_C = -10mA, V_{CE} = -1V$	100	-	300	
		$I_C = -50mA, V_{CE} = -1V$	60	-	-	
		$I_C = -100mA, V_{CE} = -1V$	30	-	-	
Collector - Emitter Saturation Voltage (Note 2)	$V_{CE(SAT)}$	$I_C = -10mA, I_B = -1mA$ $I_C = -50mA, I_B = -5mA$	-	-	-0.25 -0.4	V
Base - Emitter Saturation Voltage (Note 2)	$V_{BE(SAT)}$	$I_C = -10mA, I_B = -1mA$ $I_C = -50mA, I_B = -5mA$	-0.65 -	-	-0.85 -0.95	V
Collector - Base Capacitance	$C_{CBO}$	$V_{CB} = -5V, I_E = 0, f = 1MHz$	-	-	4.5	pF
Emitter - Base Capacitance	$C_{EBO}$	$V_{EB} = -0.5V, I_C = 0, f = 1MHz$	-	-	10	pF
Delay Time	$t_d$	$V_{CC} = -3V, V_{BE} = -0.5V,$ $I_C = -10mA, I_B = -1mA$	-	-	35	ns
Rise Time	$t_r$	$V_{CC} = -3V, V_{BE} = -0.5V,$ $I_C = -10mA, I_B = -1mA$	-	-	35	ns
Storage Time	$t_s$	$V_{CC} = -3V, I_C = -10mA$ $I_{B1} = I_{B2} = -1mA$	-	-	225	ns
Fall Time	$t_f$	$V_{CC} = -3V, I_C = -10mA$ $I_{B1} = I_{B2} = -1mA$	-	-	75	ns
Current Gain-Bandwidth Product	$f_T$	$I_C = -10mA, V_{CE} = -20V,$ $f = 100MHz$	250	-	-	MHz


Note 2: Pulse Test: Pulse Width  $\leq 300 \mu s$ , Duty Cycle  $\leq 2.0\%$ .

### SWITCHING TIME EQUIVALENT TEST CIRCUITS







**ELECTRICAL CHARACTERISTICS CURVE**




**Fig. 1. Typical  $h_{FE}$  vs. Collector Current**




**Fig. 2. Typical  $V_{BE}$  vs. Collector Current**



**Fig. 3. Typical  $V_{CE(sat)}$  vs. Collector Current**



**Fig. 4. Typical  $V_{BE(sat)}$  vs. Collector Current**



**Fig. 5. Typical Capacitances vs. Reverse Voltage**




# MMBT3906

## Product and Packing Information

Part No.	Package Type	Packing Type	Marking
MMBT3906	SOT-23	3K pcs / 7" reel	S2A

## Mounting Pad Layout





## MMBT3906

---

### Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation. Customers are responsible in comprehending the suitable use in particular applications. Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.