



## **SCHOTTKY BARRIER DIODE**

### **FEATURES**

- SOD-323HE low profile package
- Low forward voltage drop, low reverse current
- High Efficiency
- Lead free in compliance with EU RoHS 2.0
- Green molding compound as per IEC 61249 standard


## **MECHANICAL DATA**

- · Case : SOD-323HE, Plastic
- Terminals : Solderable per MIL-STD-750, Method 2026
- Apporx. Weight: 0.0002 ounces, 0.005 grams

## **APPLICATIONS**

- · Low voltage high frequency inverters
- DC/DC converters
- · Polarity protection
- Freewheeling





## ABSOLUTE MAXIMUM RATINGS (TA=25°C)

PARAMETER	SYMBOL	LIMITS	UNIT
Maximum Repetitive Peak Reverse Voltage	VRRM	30	V
Maximum Average Rectified Forward Current	lo	1	А
Peak Forward Surge Current (Half Sine Wave , 1 cycle , non-repetitive )	I FSM	22	А
Operating Junciton Temperature Range	TJW	-40 to +150	O°
Storage Temperature Range	Тѕтс	-40 to +150	°C

# ELECTRICAL CHARACTERISTICS (TA=25°C)

PARAMETER	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNITS
Forward Voltage	V <sub>F</sub> 1	I F=0.7A	-	0.42	0.45	V
	VF2	I F=1A	-	0.47	0.52	V
Reverse Current	I R1	V <sub>R</sub> =5V	-	1	-	μΑ
	I R2	VR=30V	-	10	100	μΑ
Thermal Resistance (Note)	R <sub>eja</sub>	Junction to Ambient	-	-	220	°C/W
	R <sub>eJL</sub>	Junction to Lead	-	=	50	°C/W

Note: Mounted on P.C Board with (15mmx50mm) copper pad areas.








Fig.1 Forward Current Derating Curve




Fig.2 Typical Junction Capacitance




Fig.3 Typical Reverse Characteristics





Fig.4 Typical Forward Characteristics



**Fig.5 Operating Temperature Derating Curve** 





## PART NO PACKING CODE VERSION

Part No Packing Code	Package Type	Packing Type	Marking	Version
SS1030HEWS_R1_00001	SOD-323HE	5K pcs / 7" reel	ET	Halogen free
SS1030HEWS_R2_00001	SOD-323HE	12K pcs / 13" reel	ET	Halogen free


# For example : RB500V-40\_R2\_00001 Part No. Serial number Version code means HF Packing size code means 13" Packing type means T/R

Packing Code XX			Version Code XXXXX			
Packing type	1 <sup>st</sup> Code	Packing size code	2 <sup>nd</sup> Code	HF or RoHS	1 <sup>st</sup> Code	2 <sup>nd</sup> ~5 <sup>th</sup> Code
Tape and Ammunition Box (T/B)	Α	N/A	0	HF	0	serial number
Tape and Reel (T/R)	R	7"	1	RoHS	1	serial number
Bulk Packing (B/P)	В	13"	2			
Tube Packing (T/P)	Т	26mm	X			
Tape and Reel (Right Oriented) (TRR)	S	52mm	Y			
Tape and Reel (Left Oriented) (TRL)	L	PANASERT T/B CATHODE UP (PBCU)	U			
FORMING	F	PANASERT T/B CATHODE DOWN (PBCD)	D			





# **MOUNTING PAD LAYOUT**







# **Disclaimer**

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
  of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
   Customers are responsible in comprehending the suitable use in particular applications.
   Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments requiring high level of reliability or relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, transportation equipment, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.